

Remote control for LED PAR56



- * One remote control can activate several receivers, for example, the receiver for the swimming pool or park lights, or it can be used to open the gate, awnings, etc.
- * 4lamps distributed on two parallel outlets can be connected to each receiver.
- * The maximum distance between the remote control and the receiver is 80-100 meters in free air conditions without obstructions.
- * The remote control works with a 3V CR2032 type lithium battery which is provided.
- * The remote control and receiver are available with separate codes.

Item Characteristics

Code	RCT00001
Light Tonality	Remote control for LED PAR56
Weight	25 g

Tech Info

Open fittings	YES
Lamp start time	<0,2s
T (°C) Working environment Temp.	-25°C / +35°C
Fulfilled Directives and norms	2011/65/UE * RoHS 2012/19/UE * RAEE 2014/30/UE * Compatibilità Elettromagnetica 2014/35/UE * Bassa Tensione EN 61547 * anno 2010 EN 55015 * anno 2014 EN 61000-3-2 * anno 2007 (+A1/+A2:2011) EN 61000-3-3 * anno 2014 EN 62471 * anno 2010 IEC/TR 62471-2 EN 62031 * anno 2009 (+A1:2013) EN 62560 * anno 2013 EN 60968 * anno 2013 244/2009 * Progettazione Eco Compatibile 2010/30/EU * Energy Consumption 874/2012 * Regulation for Energy Labelling 2009/125/CE * Progettazione Eco Compatibile 1194/2012 * Progettazione Eco Compatibile

Shipping info

Single pack dimensions L x H x D (mm)	45 x 785 x 24
Item barcode	8011905830410
Pack	1 pz
Master barcode	8011905775698